



Product Specification Bulletin

250 Watt

REDUCED OUTER JACKET

Clear - 10K

Phone: (866) 474-4335 Fax: (559) 733-1407

Mogul - Enclosed Luminaire
T15 Tubular Outer Jacket



MH 250W/U/T15/10K

Product Number

63897

Lamp Type

SINGLE ENDED METAL HALIDE

ANSI Designation

M58/E

Performance Data

<i>Light Output (Lumens @ 100 Hrs.)</i>	-
<i>Lamp Lumens Per Watt</i>	-
<i>Mean Output (Lumens)</i>	-
<i>Rated Life (Hrs. @ 10 Hr. / Start)</i>	8000 V / 6000 H
<i>Correlated Color Temperature K</i>	10000
<i>Chromaticity (CIE -X,Y)</i>	.222 .190
<i>Color Rendering Index (CRI)</i>	65
<i>Typical Warm Up Time (Minutes)</i>	3-5
<i>Typical Hot Restart Time (Minutes)</i>	5-10
<i>Burning Position</i>	UNIVERSAL

Physical Data / Requirements

<i>Base Designation</i>	MOGUL (E39)
<i>Bulb Designation</i>	T15 (46mm)
<i>Bulb Diameter</i>	1 7/8"
<i>Max. Overall Length (MOL)</i>	8 5/16"
<i>Light Center Length (LCL)</i>	5"
<i>Effective Arc Length</i>	27.0 mm
<i>Max. Base Temperature (°C)</i>	210
<i>Max. Bulb Temperature (°C)</i>	450
<i>Luminaire Type</i>	ENCLOSED
<i>Socket Pulse Rating (KV)</i>	-
<i>Socket Style</i>	MOGUL

Electrical Data / Requirements

<i>Lamp Wattage</i>	250
<i>Operating Voltage (Nominal)</i>	133
<i>Operating Current (Amps)</i>	2.1
<i>Min. Open Circuit Voltage (RMS)</i>	-
<i>Min. -Max. Starting Pulse (Peak V)</i>	-
<i>Min. Pulse Width At 2700 Volts (u sec)</i>	-
<i>Min. Pulse Rate Per 1/2 Cycle</i>	-
<i>Pulse Position (Min. % OCV Peak)</i>	-

Revision: 1/21/2005

2209 - 3

Notes

- ▶ Lamp operates on standard 250 watt (M58) metal halide ballast.
- ▶ Nominal color temperature rating is based on vertical (±15°) operation of the lamp. Off vertical positions will result in higher color temperature.

Lamps

THIS LAMP CONFORMS TO FEDERAL STANDARD 21 CFR 1040.30

Warning: This lamp can cause skin burn and eye inflammation from shortwave ultraviolet radiation if outer envelope of the lamp is broken or punctured. Do not use where people will remain for more than a few minutes unless adequate shielding or other safety precautions are used. Lamps that will automatically extinguish when outer envelope is broken or punctured are commercially available.